USB-4604B USB-4604BM

4-port RS-232 Serial to USB Converter with ESD Surge Protection

4-port Serial to USB Converter with ESD **Surge Protection**



Features

- Full compliance with USB V1.1 and V2.0 specifications
- RS-232/422/485 port supported
- Transmission speed up to 921.6 kbps
- Automatic RS-485 data flow control
- Bus-powered; no need for external power supply
- Plug & Play installation
- No additional IRQs or I/O ports required
- Hot swap function supported

Introduction

USB-4604 series allows PC users to connect a serial device to a system that use a USB interface. To attach the USB-4604B/4604BM to a PC, you don't need to open the chassis or power down your PC. Instantly get extra high-speed RS-232/422/485 ports. The power is derived from the USB port, so there are no power adapters to deal with. This makes the USB-4604B/4604BM especially suitable for modems, printers, POS systems and industrial control devices.

Supporting USB2.0 high speed, USB-4604B/4604BM features several powerful functions such as high-speed 921.6 kbps transmission, support for various operating systems, independent RS-232/422/485 ports and more. By simply plugging in a USB hub, USB-4604B and USB-4604BM eliminates the configuration issues associated with high-priced. older card solutions. You only have to install the drivers, no need to set cards slots, IRQ addresses, DMA channels, or device addresses. This reduces programming effort.

Specifications

General

Certifications CE, FCC (Class A)

Connectors 1 x USB Type B (Type A to Type B cable provided)

4 x DR9

ABS+PC Enclosure USB Cable Max. 15ft (4.6 m)

Insert

Power Input 10 to 48 V_{DC} (external) or 5 V_{DC} (Bus powered)

 Power Consumption 130 mA @ 5 V (Typical) 200 mA @ 5 V (Max.)

Communications

Data Bits 5, 6, 7, 8

Parity None, Odd, Even, Space, Mark

Stop Bits 1, 1.5, 2 Transmission Speed up to 921.6 kbps

Protection

 EFT Protection $2,500 V_{DC}$ ESD Protection IC Embedded 16KV

Mechanism

Dimensions 132 x 80 x 32 mm Enclosure ABS+PC - Mounting DIN-rail, panel

Software

 Driver Support Windows 2000/XP/2003, Windows CE 5.0

Environment

• Operating Temperature $0 \sim 55^{\circ} \text{ C} (32 \sim 131^{\circ} \text{ F})$ Storage Temperature -25 ~ 80° C (-13 ~ 176° F)

 Operating Humidity 20 ~ 95% RH

Ordering Information

 USB-4604B 4-port RS-232 to USB Converter w/ESD

 USB-4604BM 4-port RS-232/422/485 to USB Converter w/ESD